

**MIDI Implementation Chart V 2.0 (Page 1 of 3)**
**Manufacturer: STUDIOLOGIC**
**Model: Numa Compact 2 (Controller Section)**
**Version: 1.2.0**
**Date: 15.07.2020**

		Transmit/Export	Recognized/Import	Remarks
<i>1. Basic Information</i>				
MIDI channels		1-16	-	
Note numbers		0-127	-	
Program change		0-127	No	
Bank Select response			No	
Modes supported:	Mode 1: Omni-On, Poly Mode 2: Omni-On, Poly Mode 3: Omni-On, Poly Mode 4: Omni-On, Poly Multi Mode		No No No No No	
Note-On Velocity		Yes	No	
Note-Off Velocity		Yes	No	
Channel Aftertouch		Yes	No	Keyboard
Poly (Key) Aftertouch		No	No	
Pitch Bend		Yes	No	Stick1 X-Y
Active Sensing		No	No	
System Reset		No	No	
Tune Request		No	No	
Universal System Exclusive:	Sample Dump Standard	No	No	
	Device Inquiry	No	No	
	File Dump	No	No	
	MIDI Tuning	No	No	
	Master Volume	No	No	
	Master Balance	No	No	
	Notation Information	No	No	
	Turn GM1 System On	No	No	
	Turn GM2 System On	No	No	
	Turn GM System Off	No	No	
	DLS-1	No	No	
	File REference	No	No	
	Controller Destination	No	No	
	Key-based Instrument Ctrl	No	No	
	Master Fine/Coarse Tune	Yes	No	F0, 41, 00, 42, 12, 40, 00, 00, 00, xx, xx, xx, 00, F7
	Other Universal System Esxclusive	No	No	
Manufacturer or Non-Commercial System Exclusive		No	No	
NRPNs		No	No	
RPN 00 (Pitch Bend Sensitivity)		No	No	
RPN 01 (Channel Fine Tune)		No	No	
RPN 02 (Channel Coarse Tune)		No	No	
RPN 03 (Tuning Program Select)		No	No	
RPN 04 (Tuning Bank Select)		No	No	
RPN 05 (Modulation Depth Range)		No	No	
<i>2. MIDI Tuning and Synchronization</i>				
MIDI CLock		No	No	
Song Position Pointer		No	No	
Song Select		No	No	
Start		No	No	
Continue		No	No	
Stop		No	No	
MIDI Time Code		No	No	
MIDI Machine Control		No	No	
MIDI Show Control		No	No	
<i>3. Extension Compatibility</i>				
General MIDI comapatible		No	No	
DLS comapatible		No	No	
Standard MIDI Files		No	No	
XMF Files		No	No	
SP-MIDI compatible		No	No	

MIDI Implementation Chart V 2.0 (Page 2 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Controller Section)

Version: 1.2.0

Date: 15.07.2020

Control#	Function	Transmitted (Y/N)	Recognized (Y/N)	Remarks
0	Bank Select (MSB)	Yes	No	Zone Edit
1	Modulation Wheel (MSB)	Yes	No	Stick2 X
2	Breath Controller (MSB)	No	No	
3		No	No	
4	Foot Controller (MSB)	No	No	
5	Portamento Time (MSB)	No	No	
6	Data Entry (MSB)	No	No	
7	Channel Volume (MSB)	Yes	No	Zone Edit
8	Balance (MSB)	No	No	
9		No	No	
10	Pan (MSB)	No	No	
11	Expression (MSB)	Yes	No	Pedal 1-2
12	Effect Control 1 (MSB)	No	No	
13	Effect Control 2 (MSB)	No	No	
14		No	No	
15		No	No	
16	General Purpose Controller 1 (MSB)	No	No	
17	General Purpose Controller 2 (MSB)	No	No	
18	General Purpose Controller 3 (MSB)	No	No	
19	General Purpose Controller 4 (MSB)	No	No	
20		No	No	
21		No	No	
22		No	No	
23		No	No	
24		No	No	
25		No	No	
26		No	No	
27		No	No	
28		No	No	
29		No	No	
30		No	No	
31		No	No	
32	Bank Select (LSB)	Yes	No	Zone Edit
33	Modulation Wheel (LSB)	Yes	No	Stick2 X
34	Breath Controller (LSB)	No	No	
35		No	No	
36	Foot Controller (LSB)	No	No	
37	Portamento Time (LSB)	No	No	
38	Data Entry (LSB)	No	No	
39	Channel Volume (LSB)	Yes	No	Zone Edit
40	Balance (LSB)	No	No	
41		No	No	
42	Pan (LSB)	No	No	
43	Expression (LSB)	Yes	No	Pedal 1-2
44	Effect Control 1 (LSB)	No	No	
45	Effect Control 2 (LSB)	No	No	
46		No	No	
47		No	No	
48	General Purpose Controller 1 (LSB)	No	No	
49	General Purpose Controller 2 (LSB)	No	No	
50	General Purpose Controller 3 (LSB)	No	No	
51	General Purpose Controller 4 (LSB)	No	No	
52		No	No	
53		No	No	
54		No	No	
55		No	No	
56		No	No	
57		No	No	
58		No	No	
59		No	No	
60		No	No	
61		No	No	
62		No	No	
63		No	No	

## MIDI Implementation Chart V 2.0 (Page 3 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Controller Section)

Version: 1.2.0

Date: 15.07.2020

Control#	Function	Transmitted (Y/N)	Recognized (Y/N)	Remarks
64	Sustain Pedal	Yes	No	Pedal 2 (SLP3-D/Switch)
65	Portamento On/Off	No	No	
66	Sostenuto	Yes	No	Pedal 2 (SLP3-D)
67	Soft Pedal	Yes	No	Pedal 2 (SLP3-D)
68	Legato Footswitch	No	No	
69	Hold 2	No	No	
70	Sound Controller 1 (default: Sound Variation)	No	No	
71	Sound Controller 2 (default: Timber / Harmonic Quality)	No	No	
72	Sound Controller 3 (default: Release Time)	No	No	
73	Sound Controller 4 (default: Attack Time)	No	No	
74	Sound Controller 5 (default: Brightness)	Yes	No	Stick2 Y
75	Sound Controller 6 (GM2 default: Decay Time)	No	No	
76	Sound Controller 7 (GM2 default: Vibrato Rate)	No	No	
77	Sound Controller 8 (GM2 default: Vibrato Depth)	No	No	
78	Sound Controller 9 (GM2 default: Vibrato Delay)	No	No	
79	Sound Controller 10 (GM2 default: Undefined)	No	No	
80	General Purpose Controller 5	No	No	
81	General Purpose Controller 6	No	No	
82	General Purpose Controller 7	No	No	
83	General Purpose Controller 8	No	No	
84	Portamento Control	No	No	
85		No	No	
86		No	No	
87		No	No	
88		No	No	
89		No	No	
90		No	No	
91	Effects 1 Depth (default: Reverb Send)	No	No	
92	Effects 2 Depth (default: Tremolo Depth)	No	No	
93	Effects 3 Depth (default: Chorus Send)	No	No	
94	Effects 4 Depth (default: Celeste [Detune] Depth)	No	No	
95	Effects 5 Depth (default: Phaser Depth)	No	No	
96	Data Increment	No	No	
97	Data Decrement	No	No	
98	Non-Registered Parameter Number (LSB)	No	No	
99	Non-Registered Parameter Number (MSB)	No	No	
100	Registered Parameter Number (LSB)	No	No	
101	Registered Parameter Number (MSB)	No	No	
102	FX1 Change	No	No	
103	FX2 Change	No	No	
104	Reverb Change	No	No	
105		No	No	
106		No	No	
107		No	No	
108		No	No	
109		No	No	
110		No	No	
111		No	No	
112		No	No	
113		No	No	
114		No	No	
115		No	No	
116		No	No	
117		No	No	
118		No	No	
119		No	No	
120	All Sound Off	No	No	
121	Reset All Controllers	Yes	No	
122	Local Control On/Off	No	No	
123	All Notes Off	Yes	No	
124	Omni Mode Off	No	No	
125	Omni Mode On	No	No	
126	Poly Mode Off	No	No	
127	Poly Mode ON	No	No	

MIDI Implementation Chart V 2.0 (Page 1 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Keyboard Section – Multi Channel)

Version: 1.2.0

Date: 15.07.2020

	Transmit/Export	Recognized/Import	Remarks
<i>1. Basic Information</i>			
MIDI channels	1,2,16	1,2,16	1=Upper, 2=Lower, 16=Common Channel
Note numbers	0-127	0-127	
Program change	0-127	0-127	Preset change on common channel
Bank Select response		Yes	LSB only. See related Sound List Chart.
Modes supported:	Mode 1: Omni-On, Poly Mode 2: Omni-On, Poly Mode 3: Omni-On, Poly Mode 4: Omni-On, Poly Multi Mode	No No No No No	
Note-On Velocity	Yes	Yes	
Note-Off Velocity	Yes	Yes	
Channel Aftertouch	Yes*	Yes	*Keyboard
Poly (Key) Aftertouch	No	No	
Pitch Bend	Yes*	Yes	*Stick1 X-Y
Active Sensing	No	No	
System Reset	No	No	
Tune Request	No	No	
Universal System Exclusive:	Sample Dump Standard Device Inquiry File Dump MIDI Tuning Master Volume Master Balance Notation Information Turn GM1 System On Turn GM2 System On Turn GM System Off DLS-1 File REference Controller Destination Key-based Instrument Ctrl Master Fine/Coarse Tune Other Universal System Esxclusive	No No No No No No No No No No No No No No No Yes No	No No No No No No No No No No No No No No No No F0, 41, 00, 42, 12, 40, 00, 00, 00, xx, xx, xx, 00, F7
Manufacturer or Non-Commercial System Exclusive	No	No	
NRPNS	No	No	
RPN 00 (Pitch Bend Sensitivity)	No	No	
RPN 01 (Channel Fine Tune)	No	No	
RPN 02 (Channel Coarse Tune)	No	No	
RPN 03 (Tuning Program Select)	No	No	
RPN 04 (Tuning Bank Select)	No	No	
RPN 05 (Modulation Depth Range)	No	No	
<i>2. MIDI Tuning and Synchronization</i>			
MIDI CLock	No	No	
Song Position Pointer	No	No	
Song Select	No	No	
Start	No	No	
Continue	No	No	
Stop	No	No	
MIDI Time Code	No	No	
MIDI Machine Control	No	No	
MIDI Show Control	No	No	
<i>3. Extension Compatibility</i>			
General MIDI comapatible	No	No	
DLS comapatible	No	No	
Standard MIDI Files	No	No	
XMF Files	No	No	
SP-MIDI compatible	No	No	

## MIDI Implementation Chart V 2.0 (Page 2 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Keyboard Section – Multi Channel)

Version: 1.2.0

Date: 15.07.2020

Control#	Function	Transmitted (Y/N)	Recognized (Y/N)	Remarks
0	Bank Select (MSB)	No	No	
1	Modulation Wheel (MSB)	Yes*	Yes	*Stick2X (based on FX Autoset On/Off)
2	Breath Controller (MSB)	No	No	
3				
4	Foot Controller (MSB)	No	No	
5	Portamento Time (MSB)	No	No	
6	Data Entry (MSB)	No	No	
7	Channel Volume (MSB)	No	Yes	
8	Balance (MSB)	No	No	
9				
10	Pan (MSB)	No	No	
11	Expression (MSB)	Yes*	Yes	*Pedal 1-2 (assignable)
12	Effect Control 1 (MSB)	No	No	
13	Effect Control 2 (MSB)	No	No	
14		No	No	
15		No	No	
16	General Purpose Controller 1 (MSB)	No	No	
17	General Purpose Controller 2 (MSB)	No	No	
18	General Purpose Controller 3 (MSB)	No	No	
19	General Purpose Controller 4 (MSB)	No	No	
20		No	No	
21		No	No	
22		No	No	
23		No	No	
24		No	No	
25		No	No	
26		No	No	
27		No	No	
28		No	No	
29		No	No	
30		No	No	
31		No	No	
32	Bank Select (LSB)	No	Yes	Ch 1,2
33	Modulation Wheel (LSB)	Yes*	No	*Stick2X (based on FX Autoset On/Off)
34	Breath Controller (LSB)	No	No	
35		No	No	
36	Foot Controller (LSB)	No	No	
37	Portamento Time (LSB)	No	No	
38	Data Entry (LSB)	No	No	
39	Channel Volume (LSB)	No	No	
40	Balance (LSB)	No	No	
41		No	No	
42	Pan (LSB)	No	No	
43	Expression (LSB)	Yes*	No	*Pedal 1-2
44	Effect Control 1 (LSB)	No	No	
45	Effect Control 2 (LSB)	No	No	
46		No	No	
47		No	No	
48	General Purpose Controller 1 (LSB)	No	No	
49	General Purpose Controller 2 (LSB)	No	No	
50	General Purpose Controller 3 (LSB)	No	No	
51	General Purpose Controller 4 (LSB)	No	No	
52		No	No	
53		No	No	
54		No	No	
55		No	No	
56		No	No	
57		No	No	
58		No	No	
59		No	No	
60		No	No	
61		No	No	
62		No	No	
63		No	No	

## MIDI Implementation Chart V 2.0 (Page 3 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Keyboard Section – Multi Channel)

Version: 1.2.0

Date: 15.07.2020

Control#	Function	Transmitted (Y/N)	Recognized (Y/N)	Remarks
64	Sustain Pedal	Yes*	Yes	*Pedal 2 (SLP3-D/Switch)
65	Portamento On/Off	No	No	
66	Sostenuto	Yes*	Yes	*Pedal 2 (SLP3-D)
67	Soft Pedal	Yes*	Yes	*Pedal 2 (SLP3-D)
68	Legato Footswitch	No	No	
69	Hold 2	No	No	
70	Sound Controller 1	No	No	
71	Sound Controller 2	No	No	
72	Sound Controller 3	No	No	
73	Sound Controller 4	No	No	
74	Sound Controller 5	Yes*	No	*Stick2Y
75	Sound Controller 6	No	No	
76	Sound Controller 7	No	No	
77	Sound Controller 8	No	No	
78	Sound Controller 9	No	No	
79	Sound Controller 10	No	No	
80	General Purpose Controller 5	No	No	
81	General Purpose Controller 6	No	No	
82	General Purpose Controller 7	No	No	
83	General Purpose Controller 8	No	No	
84	Portamento Control	No	No	
85		No	No	
86		No	No	
87		No	No	
88		No	No	
89		No	No	
90		No	No	
91	Reverb Send / Reverb Level (Effects 1 Depth)	Yes	Yes*	Ch 16: Reverb Level - *Ch 1,2,3,4: Reverb Send
92	FX1 amount (wet/dry) (Effects 2 Depth)	Yes	Yes	Ch 1,2
93	FX2 amount (wet/dry) (Effects 3 Depth)	Yes	Yes	Ch 1,2
94	Effects 4 Depth (default: Celeste [Detune] Depth)	No		
95	Effects 5 Depth (default: Phaser Depth)	No		
96	Data Increment	No		
97	Data Decrement	No		
98	Non-Registered Parameter Number (LSB)	No		
99	Non-Registered Parameter Number (MSB)	No		
100	Registered Parameter Number (LSB)	No		
101	Registered Parameter Number (MSB)	No		
102	FX1 Type	Yes	Yes	Ch 1,2: 0=bypass, 1=drive, 2=chorus, 3=phaser, 4=flanger
103	FX2 Type	Yes	Yes	Ch 1,2: 0=bypass, 1=rotary, 2=tremolo, 3=pantrem, 4=delay
104	Reverb Type	Yes	Yes	Ch 16: 0=off, 1=room, 2=hall, 3=plate, 4=spring
105		No		
106		No		
107		No		
108		No		
109		No		
110	FX1 Parameter Control	Yes*	Yes	Ch 1,2 - *Stick2X (based on FX Autoset On/Off)
111	FX2 Parameter Control	Yes*	Yes	Ch 1,2 - *Stick2X (based on FX Autoset On/Off)
112		No		
113		No		
114		No		
115		No		
116		No		
117		No		
118		No		
119		No		
120	All Sound Off	No		
121	Reset All Controllers	Yes*	Yes	*on Preset Change
122	Local Control On/Off	No		
123	All Notes Off	Yes*	Yes	*on Preset Change
124	Omni Mode Off	No		
125	Omni Mode On	No		
126	Poly Mode Off	No		
127	Poly Mode ON	No		

**MIDI Implementation Chart V 2.0 (Page 1 of 3)**

**Manufacturer:** STUDIOLOGIC

**Model:** Numa Compact 2 (Keyboard Section – Single Channel)

**Version:** 1.2.0

**Date:** 15.07.2020

	Transmit/Export	Recognized/Import	Remarks
<i>1. Basic Information</i>			
<b>MIDI channels</b>	16	1,2,16	16=Common Channel
Note numbers	0-127	0-127	
Program change	0-127	0-127	Preset change on common channel
Bank Select response		Yes	LSB only. See related Sound List Chart.
Modes supported:		No	
Mode 1: Omni-On, Poly		No	
Mode 2: Omni-On, Poly		No	
Mode 3: Omni-On, Poly		No	
Mode 4: Omni-On, Poly		No	
Multi Mode		No	
Note-On Velocity	Yes	Yes	
Note-Off Velocity	Yes	Yes	
Channel Aftertouch	Yes*	Yes	*Keyboard
Poly (Key) Aftertouch	No	No	
Pitch Bend	Yes*	Yes	*Stick1 X-Y
Active Sensing	No	No	
System Reset	No	No	
Tune Request	No	No	
Universal System Exclusive:			
Sample Dump Standard	No	No	
Device Inquiry	No	No	
File Dump	No	No	
MIDI Tuning	No	No	
Master Volume	No	No	
Master Balance	No	No	
Notation Information	No	No	
Turn GM1 System On	No	No	
Turn GM2 System On	No	No	
Turn GM System Off	No	No	
DLS-1	No	No	
File REference	No	No	
Controller Destination	No	No	
Key-based Instrument Ctrl	No	No	
Master Fine/Coarse Tune	Yes	No	F0, 41, 00, 42, 12, 40, 00, 00, 00, xx, xx, xx, 00, F7
Other Universal System Exsclusive	No	No	
Manufacturer or Non-Commercial System Exclusive	No	No	
NRPNS	No	No	
RPN 00 (Pitch Bend Sensitivity)	No	No	
RPN 01 (Channel Fine Tune)	No	No	
RPN 02 (Channel Coarse Tune)	No	No	
RPN 03 (Tuning Program Select)	No	No	
RPN 04 (Tuning Bank Select)	No	No	
RPN 05 (Modulation Depth Range)	No	No	
<i>2. MIDI Tuning and Synchronization</i>			
MIDI CLock	No	No	
Song Position Pointer	No	No	
Song Select	No	No	
Start	No	No	
Continue	No	No	
Stop	No	No	
MIDI Time Code	No	No	
MIDI Machine Control	No	No	
MIDI Show Control	No	No	
<i>3. Extension Compatibility</i>			
General MIDI comapatible	No	No	
DLS comapatible	No	No	
Standard MIDI Files	No	No	
XMF Files	No	No	
SP-MIDI compatible	No	No	

## MIDI Implementation Chart V 2.0 (Page 2 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Keyboard Section – Single Channel)

Version: 1.2.0

Date: 15.07.2020

Control#	Function	Transmitted (Y/N)	Recognized (Y/N)	Remarks
0	Bank Select (MSB)	No	No	
1	Modulation Wheel (MSB)	Yes*	Yes	*Stick2X
2	Breath Controller (MSB)	No	No	
3				
4	Foot Controller (MSB)	No	No	
5	Portamento Time (MSB)	No	No	
6	Data Entry (MSB)	No	No	
7	Channel Volume (MSB)	No	Yes	
8	Balance (MSB)	No	No	
9				
10	Pan (MSB)	No	No	
11	Expression (MSB)	Yes*	Yes	*Pedal 1-2 (assignable)
12	Effect Control 1 (MSB)	No	No	
13	Effect Control 2 (MSB)	No	No	
14		No	No	
15		No	No	
16	General Purpose Controller 1 (MSB)	No	No	
17	General Purpose Controller 2 (MSB)	No	No	
18	General Purpose Controller 3 (MSB)	No	No	
19	General Purpose Controller 4 (MSB)	No	No	
20		No	No	
21		No	No	
22		No	No	
23		No	No	
24		No	No	
25		No	No	
26		No	No	
27		No	No	
28		No	No	
29		No	No	
30		No	No	
31		No	No	
32	Bank Select (LSB)	No	Yes	Ch 1,2
33	Modulation Wheel (LSB)	Yes*	No	*Stick2X
34	Breath Controller (LSB)	No	No	
35		No	No	
36	Foot Controller (LSB)	No	No	
37	Portamento Time (LSB)	No	No	
38	Data Entry (LSB)	No	No	
39	Channel Volume (LSB)	No	No	
40	Balance (LSB)	No	No	
41		No	No	
42	Pan (LSB)	No	No	
43	Expression (LSB)	Yes*	No	*Pedal 1-2 (assignable)
44	Effect Control 1 (LSB)	No	No	
45	Effect Control 2 (LSB)	No	No	
46		No	No	
47		No	No	
48	General Purpose Controller 1 (LSB)	No	No	
49	General Purpose Controller 2 (LSB)	No	No	
50	General Purpose Controller 3 (LSB)	No	No	
51	General Purpose Controller 4 (LSB)	No	No	
52		No	No	
53		No	No	
54		No	No	
55		No	No	
56		No	No	
57		No	No	
58		No	No	
59		No	No	
60		No	No	
61		No	No	
62		No	No	
63		No	No	



## MIDI Implementation Chart V 2.0 (Page 3 of 3)

Manufacturer: STUDIOLOGIC

Model: Numa Compact 2 (Keyboard Section – Single Channel)

Version: 1.2.0

Date: 15.07.2020

Control#	Function	Transmitted (Y/N)	Recognized (Y/N)	Remarks
64	Sustain Pedal	Yes*	Yes	*Pedal 2 (SLP3-D/Switch)
65	Portamento On/Off	No	No	
66	Sostenuto	Yes*	Yes	*Pedal 2 (SLP3-D)
67	Soft Pedal	Yes*	Yes	*Pedal 2 (SLP3-D)
68	Legato Footswitch	No	No	
69	Hold 2	No	No	
70	Sound Controller 1	No	No	
71	Sound Controller 2	No	No	
72	Sound Controller 3	No	No	
73	Sound Controller 4	No	No	
74	Sound Controller 5	Yes*	No	*Stick2Y
75	Sound Controller 6	No	No	
76	Sound Controller 7	No	No	
77	Sound Controller 8	No	No	
78	Sound Controller 9	No	No	
79	Sound Controller 10	No	No	
80	General Purpose Controller 5	No	No	
81	General Purpose Controller 6	No	No	
82	General Purpose Controller 7	No	No	
83	General Purpose Controller 8	No	No	
84	Portamento Control	No	No	
85		No	No	
86		No	No	
87		No	No	
88		No	No	
89		No	No	
90		No	No	
91	Effects 1 Depth → <i>Reverb Send / Reverb Level</i>	Yes	Yes*	Ch 16: Reverb Level - *Ch 1,2,3,4: Reverb Send
92	Effects 2 Depth → <i>FX1 amount (wet/dry)</i>	Yes	Yes*	*Ch 1,2
93	Effects 3 Depth → <i>FX2 amount (wet/dry)</i>	Yes	Yes*	*Ch 1,2
94	Effects 4 Depth (default: Celeste [Detune] Depth)	No		
95	Effects 5 Depth (default: Phaser Depth)	No		
96	Data Increment	No		
97	Data Decrement	No		
98	Non-Registered Parameter Number (LSB)	No		
99	Non-Registered Parameter Number (MSB)	No		
100	Registered Parameter Number (LSB)	No		
101	Registered Parameter Number (MSB)	No		
102	<i>FX1 Type</i>	Yes	Yes*	*Ch 1,2: 0=bypass, 1=drive, 2=chorus, 3=phaser, 4=flanger
103	<i>FX2 Type</i>	Yes	Yes*	*Ch 1,2: 0=bypass, 1=rotary, 2=tremolo, 3=pantrem, 4=delay
104	<i>Reverb Type</i>	Yes	Yes	Ch 16: 0=off, 1=room, 2=hall, 3=plate, 4=spring
105		No		
106		No		
107		No		
108		No		
109		No		
110	<i>FX1 Parameter Control</i>	No	Yes*	*Ch 1,2
111	<i>FX2 Parameter Control</i>	No	Yes*	*Ch 1,2
112		No		
113		No		
114		No		
115		No		
116		No		
117		No		
118		No		
119		No		
120	All Sound Off	No		
121	Reset All Controllers	Yes*	Yes	*on Preset Change
122	Local Control On/Off	No		
123	All Notes Off	Yes*	Yes	*on Preset Change
124	Omni Mode Off	No		
125	Omni Mode On	No		
126	Poly Mode Off	No		
127	Poly Mode ON	No		